

## Booster 12-24V 6200A/3100A

Reference : OE 5052



**Item name** Booster 12-24V 6200A/3100A

**Bar code** 3700461494314

**Product highlight** Mobile and powerful

**Specifications** Specifications :

- peak current (HPCA): 2540A (12V) / 1270A (24V)
- starting current (AC): 1580A (12V) / 790A (24V)
- cold start current (CCA): 1040-1100A (12V) / 520-550A (24V)
- capacity: 2x33Ah (12V) / 33Ah (24V)
- cables: 50mm<sup>2</sup>, L.165cm
- integrated cigar-lighter socket
- charging time: 4-8h
- digital voltmeter charge indicator
- battery: AGM
- weight: 29kg
- dimensions: 410x280x550mm

**Warranty period** 2 years

**Voltage** 12-24V

**Product weight (kg)** 29 kg

**Tariff code** Tariff Normal (TN)

**Warranty Procedure**DIAGNOSTIC

## Quick tip videos

Cliquez sur l'opération qui vous intéresse pour voir la **vidéo**:



[REEMPLACEMENT DU FUSIBLE D'UN BOOSTER 12 V](#)



**\*Public price Exl. Tax : €1,490**

\*Applicable user fees from 01/09/2025 to 31/08/2026

CLAS EQUIPEMENTS  
83, chemin de la CROUZA  
73800 CHIGNIN  
France

Tel : +33 (0) 4 79 72 62 22  
Fax :

Monday to Friday - From 8 to 12h  
and from 13h30 to 17h30 (16h30 on  
Friday)