

Booster 12-24V 6200A/3100A

Reference : OE 5052



Item name Booster 12-24V 6200A/3100A

Bar code 3700461494314

Product highlight Mobile and powerful

Specifications Specifications :

- peak current (HPCA): 2540A (12V) / 1270A (24V)
- starting current (AC): 1580A (12V) / 790A (24V)
- cold start current (CCA): 1040-1100A (12V) / 520-550A (24V)
- capacity: 2x33Ah (12V) / 33Ah (24V)
- cables: 50mm², L.165cm
- integrated cigar-lighter socket
- charging time: 4-8h
- digital voltmeter charge indicator
- battery: AGM
- weight: 29kg
- dimensions: 410x280x550mm

Warranty period 2 years

Voltage 12-24V

Product weight (kg) 29 kg

Tariff code Tariff Normal (TN)

Warranty Procedure DIAGNOSTIC

Quick tip videos

Cliquez sur l'opération qui vous intéresse pour voir la **vidéo**:



[REEMPLACEMENT DU FUSIBLE D'UN BOOSTER 12 V](#)



TN

CLAS EQUIPEMENTS
83, chemin de la CROUZA
73800 CHIGNIN
France

Tel : +33 (0) 4 79 72 62 22
Fax :

Monday to Friday - From 8 to 12h
and from 13h30 to 17h30 (16h30 on
Friday)